

INSULATED TENSION UNITS

Part Numbers Listed Next to the Product Photographs

P/N 12312-D
P/N 12312-1D
P/N 16515

P/N 5ARM300-7CN-3
P/N 5ARM300-1CN-3
P/N 5ARM300-6CNL-3
P/N 5ARM300-8CN-1

P/N 5ARM300-7CN
P/N 5ARM300-1CN
P/N 5ARM300-6CNL

P/N 12312



Part Number	Spring Travel cm / (in)	Starting Force kg / (lbs.)	Mid Stroke Force kg / (lbs.)	Full Stroke Force kg / (lbs.)	Maximum Load kg / (lbs.)	Tube Diameter cm / (in)	Antenna Wire Attachment*	Antenna Wire (P/N)	Attachment Means	Capacitance (pF)	Length cm / (in)	Weight g / (Oz)
12312-D	2.85 (1.125)	3.56 (8)	6.80 (15)	11.34 (25)	200.45 (450)	1.58 (.62)	Chuck Jaw Pin	14379	Eye	1	31.75 (12.5)	130 (4.6)
12312-1D	1.27 (.5)	11.34 (25)	178 (40)	22.68 (50)	200.45 (450)	1.58 (.62)	Chuck Jaw Pin	14379	Eye	1	31.75 (12.5)	130 (4.6)
12312	2.85 (1.12)	3.56 (8)	6.80 (15)	11.34 (25)	200.45 (450)	1.58 (.62)	Pin	14379	Eye	1	17.78 (7)	130 (4.6)
13352-A	1.90 (.75)	4.53 (10)	16.92 (38)	29.48 (65)	68.0 (150)	1.58 (.62)	Chuck Jaws	14379	Eye	1	19.05 (7.5)	110 (3.9)
16515	2.85 (1.125)	3.56 (8)	6.80 (15)	9.07 (20)	158.7 (350)	1.58 (.62)	Chuck Jaws	14379	Eye	1	31.51 (12.41)	130 (4.6)
5ARM300-8CN-1	2.85 (1.12)	3.56 (8)	6.80 (15)	9.07 (20)	226.80 (400)	1.11 (.44)	Chuck Jaws	14379	Quick Disconnect	1	18.09 (7.18)	56 (2)
5ARM300-7CN	2.54 (1)	3.56 (8)	6.80 (15)	9.07 (20)	113.40 (250)	1.11 (.44)	Chuck Jaws	14379	Eye	1	20.32 (8)	78 (2.75)
5ARM300-1CN	2.54 (1)	6.80 (15)	11.34 (25)	13.60 (30)	181.44 (400)	1.11 (.44)	Chuck Jaws	14379	Eye	1	20.32 (8)	50 (1.77)
5ARM300-6CNL	6.35 (2.5)	4.53 (10)	11.34 (25)	31.75 (70)	113.40 (250)	1.11 (.44)	Chuck Jaws	14379	Eye	1	30.48 (12)	110 (3.9)
5ARM300-7CN-3	2.54 (1)	3.56 (8)	11.34 (25)	9.07 (20)	113.40 (250)	1.11 (.44)	Chuck Jaws	14379	Quick Disconnect	1	21.59 (8.5)	78 (2.75)
5ARM300-1CN-3	2.54 (1)	6.80 (15)	15.87 (35)	13.60 (30)	181.44 (400)	1.11 (.44)	Chuck Jaws	14379	Quick Disconnect	1	21.59 (8.5)	60 (2.13)
5ARM300-6CNL-3	6.35 (2.5)	4.53 (10)	9.07 (20)	31.75 (70)	113.40 (250)	1.11 (.44)	Chuck Jaws	14379	Quick Disconnect	1	31.75 (12.5)	120 (4.25)